

FN-LCD-S - SERIAL LCD ANNUNCIATOR



DESCRIPTION

The FN-LCD-S serial annunciator provides a convenient and cost effective remote annunciator solution. Up to 15 FN-LCD-S annunciators can be connected to the slave RS-485 port of the FireNET control panel or network annunciator. The FN-LCD-S's large 320 character display and navigation buttons are a complete mimic of the FireNET control panel display. The use of a common interface allows the user to easily operate the FN-LCD-S as if he were operating the FireNET control panel directly.

Security is established by the use of a password or firefighters enable key. Designed to be aesthetically pleasing, the FN-LCD-S is available in charcoal grey or red enclosures. The FN-LCD-S can be surface or flush mounted without the need for a trim ring.

PRODUCT LISTINGS

UL 864, NFPA 70 & 72:
Signaling Device


 S8255 Vol. 2

STANDARD FEATURES

- UL 864 9th edition Listed
- Large 320 character liquid crystal display (8 line x 40 character) allows viewing of system status
- LED indicators for Fire, Supervisory Alarm, Pre-Alarm, Fire Output Active, AC Power On, On Test, Panel Sounder Silenced, Delay Active, More Events, Point Bypassed, General Trouble, Power Trouble, System Trouble & NAC Trouble
- Same controls as the FireNET fire panel (Reset, Panel Sounder Silence, Lamp Test, Alarm Silence, Re-sound Alarm, Fire Drill, Programmable Function, More Events, More Fire Events, Enter & Exit)
- Up to 15 FN-LCD-S serial annunciators may be connected to a FireNET control panel or network annunciator
- Resides on the FireNET slave RS-485 line
- Local piezo sounder for event notification
- Supports user codes & firefighter key to enable access & controls
- Powered by FireNET Aux 24VDC or UL fire listed Aux. 24VDC supply
- Available in red or charcoal, and can be surface or flush mounted
- Built-in help & alarm information screens
- Fire drill function

SPECIFICATIONS

Current Draw	
Standby:	20mA @ 24VDC
Alarm:	110mA @ 24VDC
Dimensions	
FN-LCD-S	10.88" W x 8.00" H x 1.38" D
Back Box	10.38" W x 7.38" H x 1.25" D
Weight	3.5 lbs
Color	Red (optional charcoal)
Material	ABS/steel enclosure
Display	8 line x 40 character LCD (320 characters total)
Network	RS485 port

Specifications subject to change without notice.

Continued on back.

ENGINEERING SPECIFICATION

The contractor shall furnish and install where indicated on the plans, the serial remote annunciator model FN-LCD-S. The FN-LCD-S shall connect to the FireNET fire alarm control panel (FACP) or network annunciator (FN-LCD-N) RS485 slave bus. The serial remote annunciator shall announce on its 320 character display and local buzzer, the condition of its master FireNET FACP. Up to 15 FN-LCD-S serial annunciators may be connected together on a single RS-485 FireNET slave bus. The FN-LCD-S shall be UL listed and compatible with the Hochiki FireNET control panel, and have surface or flush mount capability.

WIRING DIAGRAM

